# **SV 105A Hand-Arm Vibration Accelerometer**

The SV 105A accelerometer is dedicated for hand-arm vibration measurements with the SV 106 human vibration analyser. The accelerometer have a built-in memory (TEDS) containing information about the sensitivity that is automatically transferred to the SV 106 instrument.

The SV 105A should be worn directly on the operator's hand. The accelerometer has a high shock resistance, no DC-shift effect and consume much less energy than IEPE / ICP sensors.



# **Technical Specifications**

Number of Axes	3
Sensitivity (± 5 %)	0.661 mV/ms <sup>-2</sup> at 79.58 Hz
Measurement Range	2000 ms <sup>-2</sup> PEAK
Frequency Response (by design guideline, ± 3 dB)	0 Hz ÷ 1500 Hz
Resonant Frequency	16.5 kHz (MEMS transducer)
Electrical Noise	< 0.14 ms <sup>-2</sup> RMS. Wh weighting

#### Electrical:

Supply Current	_< 5.0 mA
Supply Voltage	_3.3 V ÷ 5.5 V
Bias Voltage	_1.5 V ± 0.05 V
Output Impedance	_51 Ohms
Charge / Discharge Time Constant (start-up time)	_30 sec. typ.
TEDS Memory	_installed (power supply pin)

## **Environmental Conditions:**

Maximum Vibration	_100 000 ms <sup>-2</sup> shock survival for MEMS sensor
Temperature Coefficient	_<+/-0.02 %/°C
Temperature	_from -10 °C to +50 °C
Humidity	up to 90 % RH, non-condensed

Physical:	
Sensing Element	MEMS
Cable	integrated 1.4 meters
Connector	LEMO 5-pin plug (SV 106 compatible)
Dimensions	69.6 mm x 31.4 mm, thickness from 8.3 mm to 15 mm
Weight	50-60 grams (including cable and one of the vibration contact adapters)

### Accessories:

SA 105A (optional)	calibration adap	pter

The policy of our company is to continually innovate and develop our products. Therefore, we reserve the right to change the specifications without prior notice.

